



Product: 2018-LED

Release Date: June 05, 2007

Scope: This bulletin applies only to the LED version of the 2018.

Issue 1: Short Yellow Clearance Fault when Entering Load Switch Flash

Symptom: When entering a load switch flash condition that displayed a yellow flash for at least one channel, the monitor may trip to the fault condition with a Short Yellow fault.

Root Cause: The monitor started its Short Clearance timer on the end of a green or the start of a yellow. The correct method is to start the Short Clearance timer on the end of green only.

Operational Issues: The monitor may trip to the fault condition when a load switch flash with yellows flashing is displayed. This may make it impractical to use a load switch flash with flashing yellows due to the nuisance faults.

Corrective Action: Upgrade to Firmware version 01.03.03 or greater.